


COVE – Wall Lamp




Quick Info

- General Lighting
- Bridgelux LED: 5W, CRI>90
- CCT: 3000K Available as Standard
- Beam Angle: 90°
- Lumen Output: Up to 490lm System Luminous Flux
- LED Driver: On-Off, Phase Dim, DALI Dim

Light Distribution



Finish



Order Info

LED Power	System Power	LED Voltage	LED Current	CRI	CCT	Beam	System Output	Code
5W	6W	36V	150mA	90	3000K	90°	490lm	COVD-9309006F-CB COVD-9309006F-CG COVD-9309006P-CB COVD-9309006P-CG COVD-9309006D-CB COVD-9309006D-CG
Code Remark: F=F(ON-OFF) P=P(Phase Dim) D=D(DALI Dim)								

Coding

Model	CRI/ CCT	Beam Angle	Power	Control	Finish	Reflector Color	Accessory
COVD	930	90	06	F	CB		
COVE	CRI90/ 3000K	90°	6W	On-Off	Champagne Black		
				P	CG		
				Phase Dim	Champagne Gold		
				D			
				DALI Dim			



Project: Application reference